

CO2 sensor

11086098

3-phase 6A autotransformer



Product description

The 3-phase autotransformer is a voltage controller for 1-speed asynchronous 3-phase 400 V motor supporting voltage control.

Fields of application

New, Refurbishment, Non-residential buildings

Installation

0

Reference arguments

- Voltage controller designed for 1-speed 3-phase asynchronous motor 400V, compatible with voltage control.
- Compatible with VIK, TAVA and TAHA.

Main characteristics

- metal box IP55 epoxy coating,
- hinged door,
- 5-position + On/Off manual switch (130 - 180 - 230 - 300 - 400 V),
- power on light,
- no motor protection.

Dimensional data

Variants	Height (mm)	Width (mm)	Depth (mm)	Weight (kg)
11086098	400	300	200	27,7